

# tonerbenefit

# Your Efficient 3-in-1 Mono Laser Printer

More toner - more prints - more savings

IL DEBUG DE LE DE

brother

# **DCP-B7600D**



www.brother.eu

## Your Efficient 3-in-1 Mono Laser Printer

Work smarter at home or in the office with the easily connected Brother DCP-B7600D, delivering fast flawless printing, automatic 2-sided print, quick scan speeds, a generous paper tray capacity, plus a 3 year warranty.

This 3-in-1 mono laser printer is a great choice for higher volume printing with toner cartridges printing up to 2,000 pages<sup>7</sup>. The tonerbenefit DCP-B7600D provides a lower total cost of ownership and does not compromise on quality.

# DCP-B7600D



## Key features:

- Print up to 34 pages per minute
- 2-Sided print, up to 16 sides per minute
- 2 Line LCD control panel
- USB connection
- 256MB Internal memory
- 250 Sheet paper input tray<sup>11</sup>
- Comes with 2,000 page yield toner
- 2,000 maximum yield available<sup>7</sup>

# Work smarterThe DCP-B7600D is designed to increase efficiency, with fast print speeds helping you to work<br/>smarter. The 2-sided print feature saves you time, enabling you to get on with other tasks. Scan your<br/>documents in colour or mono and send directly to your desktop or mobile device.EffortlessMake your day easier and your printing effortless, with simple set up and USB connection.<br/>This efficient DCP-B7600D is a breeze to operate using the easy to navigate control panel.The perfect<br/>partnerHigh quality print technology ensures that your output is flawless and professional every time.<br/>The expertly designed DCP-B7600D has a high capacity paper input and output tray allowing you to<br/>print for longer, while the compact and quiet form enables you to work without interruption in<br/>smaller workspaces.


Print longer

The DCP-B7600D keeps your printing costs down with the high quality economical 2,000 pages<sup>7</sup> toner cartridge, supporting your higher print volume needs and reducing your cost per page and frequency to replace.

# Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The DCP-B7600D provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.



General

**Technology** Electrophotographic Laser

Memory 256MB **Control panel** 2 Line LCD with keys

Local Interface Hi-Speed USB 2.0

#### Carton Contents

Device, Inbox Toner, Drum, Power Supply Cord, Quick Set-Up Guide, Warranty Card

**Print** 

Print Speed (A4) 1-Sided: 34ppm Mono 2-Sided: 16 sides per minute Mono

**FPOT** (First Print Out Time) Up to 8.5 Seconds Mono

**Quiet Mode** A mode to reduce the printing noise **Resolution** Up to 1200 x 1200dpi

**Print Languages** PCL6, BR-Script3, PDF Version 1.7

**Embedded Fonts (PCL)** 73 scalable fonts, 12 bitmap fonts

# Embedded Barcodes (PCL)

16 bar codes\* \*Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

**Embedded Fonts** (Postscript) 66 scalable fonts

Printer Functions

#### N-up Printing

Reduce up to 25 pages into a single page

#### Poster Printing

Enlarge a single page into a poster using 2x2, 3x3, 4x4 or 5x5 pages

#### **Toner Save Mode**

Use the Toner Save Mode to reduce toner consumption without affecting print speed

#### Watermark Printing

Watermark your documents with predefined text, custom logo or custom messages

#### ID Printing

Add identification to your printed documents (date and time, short custom message or PC username)

#### **Booklet Printing**

Print documents in A5 booklet format using automatic or manual 2-sided print

#### **Print Profiles**

Store your favourite driver settings as profiles to easily recall them

#### Manual 2-Sided Print

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

#### **Reverse Print**

Rotate the content of a printed document by 180°

Printer Driver Windows 11 (32 and 64 bit editions) and more

Linux CUPS, LPD/LPRng (x86/x64 environment) PCL Driver Universal Printer Driver (Windows) (PCL5e/BRScript)

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

#### Paper Handling<sup>11</sup>

Paper Input Standard Tray 250 Sheets

Manual Feed Slot 1 Sheet

Paper Output 120 Sheets A4

**Envelope Printing** Yes from manual feed slot Media Sizes Standard Tray A4, Letter, B5(JIS), B5(ISO), A5, A5(Long Edge), B6(JIS), A6, Executive, A4 Short, 16K(195x270mm)

Manual Feed Slot Width 76.2 to 215.9 mm, Length 127 to 355.6 mm Envelope; COM-10, DL, C5, Monarch

Scanner Glass Up to A4/LTR

Auto 2-Sided

#### Media Type and Weights Standard Tray

Plain Paper, Thin Paper, Recycled Paper, Thick Paper 60-163gsm

#### Manual Feed Slot

Plain Paper, Thin Paper, Thick Paper, Thicker Paper, Recycled Paper, Bond, Label, Envelope, Env. Thin, Env. Thick 60-230gsm

Auto 2-Sided Plain Paper, Thin Paper, Recycled Paper 64-105gsm

Сору

Copy Speed (A4) 1-Sided: 34ppm Mono

**Resolution** Up to 600 x 600dpi

#### FCOT (First Copy Out Time) Up to 10 Seconds Mono

**Grey Scale** 256 shades of grey

Copy Functions Multi-Copying/Stack/Sort Makes up to 99 copies of each page / Stacks or Sorts

# Enlargement/Reduction Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

#### N in 1 Copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet Scanner Type CIS (Contact Image Sensor)

Colour and Mono Scanning Yes

Scan Speed (A4)<sup>3</sup> 1-Sided: 22.5ipm Mono and 7.5ipm Colour Scan Resolution from Scanner Glass 1200 x 1200dpi

Interpolated Scan Resolution Brother Scanner Utility enhances up to 19,200 x 19,200 dpi

#### Colour Depth

30 bit colour Processing (Input) 24 bit colour Processing (Output)

#### **Grey Scale**

10 bit colour Processing (Input) 8 bit colour Processing (Output)

#### Scanner Functions

Supported File Formats Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable<sup>17</sup>) JPEG,TIFF Standard Functions<sup>17</sup> Scan to E-mail, OCR , Image, File **Network Scanning<sup>16</sup>** Scan to Sharepoint (iPrint&Scan for Windows only)

Scanner Drivers Windows TWAIN and WIA Windows 11 (32 and 64 bit editions)

Linux SANE (32 and 64 bit editions)

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Fleet Management Tools

BRAdmin<sup>16,17</sup> LAN/WAN management software **Embedded Web Server** Web based print management software embedded onto the device **Status Monitor**<sup>16</sup> Monitor the status of your machine from your computer

#### Software

#### Brother iPrint&Scan Desktop<sup>15,17</sup>

Print from, scan to, preview copies and check the machine status from Windows or macOS PC

#### PaperPort SE 14<sup>16,17</sup>

Document management and sharing program from KOFAX

#### Utilities

Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

#### **Easy Setup**

Simple access to drivers and software for the installation of your Brother machine from support.brother.com Windows/Mac

#### Connectivity

Local Interface Hi-Speed USB 2.0

#### **Security Features**

#### Automatic Intrusion Detection

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, to ensure the device remains secure

#### Firmware Updates

Manually download updates to install the latest version

#### Supplies and Consumables

Inbox Toner<sup>7</sup> 1 x 2,000 pages (BK) Drum Unit DR B023 Approx 12,000 pages

at 1 pages per job

Standard Yield Toner<sup>7</sup> TNB023 - 2,000 pages

Dimensions and Weights **With Carton (WxDxH)** 580 x 517 x 434mm - 13.00kg **Without Carton (WxDxH)** 410 x 399 x 272mm - 9.20kg

**Duty Cycle** 

Recommended Monthly Up to 2,500 pages

Operating Environment Power Requirement 220-240V AC 50/60Hz **Operating Environment** Humidity 20 - 80 % 10°C - 32.5°C

### Storage Environment

Humidity 35 - 85 % 0°C - 40°C 32°F - 104°F

#### Environment

Approx Power Consumption<sup>13,23</sup> Copying: 490W Copying in quiet mode: 280W Printing: 470W Printing in quiet mode: 270W Ready: 43W Sleep: 4.1W Deep Sleep: 0.5W Power Off: 0.08W **TEC Value** 0.39 kWh/week

50°F - 90.5°F

#### Sound Power<sup>12</sup>

Printing: 6.63B(A) Ready: Inaudible Quiet Mode: 6.12B(A) Deep Sleep: Inaudible

#### Sound Pressure<sup>12</sup>

PC Printing (Mono): Approx. 49.0dB(A) Ready: 30.0db(A) Quiet Mode: 44.0db(A)

#### **Toner Save**

This reduces the toner consumption to get more pages from your consumables

- 3 Scan Speeds based on ISO/IEC 17991
- 7 Approx. declared yield value in accordance with ISO/IEC 19752
- 11 Capacity calculated with 80gsm paper
- 12 Sound pressure and sound power level in accordance with ISO 7779
- 13 Power consumption power off is measured according to IEC 62301 Edition 2.0
- 15 Windows and macOS only
- 16 Windows only
- 17 Optional download
- 18 Requires an Internet connection
- 23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration







#### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

> brother at your side